

# Circuit separators

## Separator end sections (cont.)

Product	Type	Order P/N
---------	------	-----------




With possibility of mounting a protective cover **CPV**, and a marker-holder **PEP**. Snap on mounting on PR1, PR3, PR4 and PR5 rails.  
 For blocks :  
**MA 2,5/5 - M 4/6 - M 6/8 - M 10/10 - M 16/12 - M 35/16 (1)**  
**M 6/8.STA - M 6/8.SF (2)**  
**M 70/22 - M 10/12.SF - MB 10/24.SF - MB 25/30.SF -**  
**MU 10/13 - M 10/13.TSF (3)**  
**M 6/8.ST (4)**  
 Thickness : 3 mm .118"

Product	Type	Order P/N
Separator end section	grey <input type="checkbox"/> <b>SCFCV1-2 (1)</b>	1SNA 116 795 R1100
	grey <input type="checkbox"/> <b>SCFCV3 (2)</b>	1SNA 116 796 R1200
	grey <input type="checkbox"/> <b>SCFCV4 (3)</b>	1SNA 116 797 R1300
	grey <input type="checkbox"/> <b>SCFCV5 (4)</b>	1SNA 116 798 R2400

### Accessories :

Protective cover of transparent PVC, length 1 m 3'3" (39") approx.  
 For cover mounting, place a separator end section **SCFCV** every 400 mm approx., at terminal assembly extremities. It can also be used for marking the terminal unit by means of a blank marker strip **RTC**, which sticks under the cover.



**RTC width : 20 mm .79"**  
**RTC length : 1 m 39"**

Separator	Cover	Width	Height
<b>SCFCV1-2</b>	<b>CPV1-2</b>	73 mm 2.87"	┌ 66 mm 2.62"
			└ 74 mm 2.91"
			└ 72 mm 2.83"
<b>SCFCV3</b>	<b>CPV3</b>	85 mm 3.35"	┌ 68,5 mm 2.70"
			└ 76 mm 2.99"
			└ 74 mm 2.91"
<b>SCFCV4</b>	<b>CPV4-S</b>	85 mm 3.35"	┌ 68,5 mm 2.70"
			└ 76 mm 2.99"
			└ 74 mm 2.91"
<b>SCFCV5</b>	<b>CPV4-S</b>	104 mm 4.09"	┌ 72 mm 2.83"
			└ 79,5 mm 3.13"
			└ 77,5 mm 3.05"

Protective cover	clear	<b>CPV1-2</b>	1SNA 176 816 R1200
	clear	<b>CPV3</b>	1SNA 176 817 R1300
	clear	<b>CPV4-S</b>	1SNA 176 791 R2100
Top marking strip		<b>RTC</b>	1SNA 163 156 R2700
Marker holder		<b>PEP</b>	1SNA 113 762 R2400



**PEP**

This marker holder snaps on separator end section **SCFCV**.  
 It can receive 1 label **RC610**.